

L77F/PL77-LAK8

L77F/PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill LAK 500, 1000, 2000, 5000, 10000, 20000, 50000, 100000 8bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / LAK 500	OFF	OFF	OFF							
2 Pulse / LAK 500	OFF	OFF	ON							
3 Pulse / LAK 500	OFF	ON	OFF							
4 Pulse / LAK 500	OFF	ON	ON							
5 Pulse / LAK 500	ON	OFF	OFF							
10 Pulse / LAK 500	ON	OFF	ON							
20 Pulse / LAK 500	ON	ON	OFF							
100 Pulse / LAK 500	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept LAK 500 & 1000						ON				
Reject LAK 500 & 1000						OFF				
★ Accept LAK 2000 & 5000							ON			
Reject LAK 2000 & 5000							OFF			
★ Accept LAK 10000 & 20000								ON		
Reject LAK 10000 & 20000								OFF		
★ Accept LAK 50000									ON	
Reject LAK 50000									OFF	
★ Accept LAK 100000										ON
Reject LAK 100000										OFF

★ Manufacture setting

Note : (1) Please reset the bill acceptor after set the dip switch.
(2) With stacker: not accept 100000(2020)

L77F&PL77-LAK8(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
BV1	LAK 500	LAK 500	LAK 500	LAK 500
BV2	LAK 1000	LAK 1000	LAK 1000	LAK 1000
BV3	LAK 2000	LAK 2000	LAK 2000	LAK 2000
BV4	LAK 5000	LAK 5000	LAK 5000	LAK 5000
BV5	LAK 10000	LAK 10000	LAK 10000	LAK 10000
BV6	LAK 20000	LAK 20000	LAK 20000	LAK 20000
BV7	LAK 50000	LAK 50000	LAK 50000	LAK 50000
BV8	LAK100000	LAK100000	LAK100000	LAK100000

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting