

L77F/PL77-SBD6

L77F/PL77 Option Switch Settings : 1(Pulse/RS232 A0/ccNet/ICT104U)

Supported bill SBD 5, 10, 20, 40, 50, 100 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / SBD 5	OFF	OFF	OFF							
2 Pulses / SBD 5	OFF	OFF	ON							
3 Pulses / SBD 5	OFF	ON	OFF							
4 Pulses / SBD 5	OFF	ON	ON							
5 Pulses / SBD 5	ON	OFF	OFF							
10 Pulses / SBD 5	ON	OFF	ON							
20 Pulses / SBD 5	ON	ON	OFF							
100 Pulses / SBD 5	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept SBD 5 & 10 & 20						ON				
Reject SBD 5 & 10 & 20						OFF				
★ Accept SBD 40							ON			
Reject SBD 40							OFF			
★ Accept SBD 50								ON		
Reject SBD 50								OFF		
★ Accept SBD 100									ON	
Reject SBD 100									OFF	
Simulation BillBox Has Been Removed										ON
★ Default										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

Currency Assign Data

Interface Bill value	Pulse	RS232 A0	ccNet	ICT104U
BV1	SBD 5	SBD 5	SBD 5	SBD 5
BV2	SBD 10	SBD 10	SBD 10	SBD 10
BV3	SBD 20	SBD 20	SBD 20	SBD 20

Interface Bill value	Pulse	RS232 A0	ccNet	ICT104U
BV4	SBD 40	SBD 50	SBD 40	SBD 40
BV5	SBD 50	SBD 100	SBD 50	SBD 50
BV6	SBD 100	SBD 40	SBD 100	SBD 100

L77F/PL77-SBD6(Pulse/RS232 A0/ccNet/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
RS232 A0 Mode		ON	ON	
★ Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Reserved
2	Reserved
3	\$A 5
4	\$A 10
5	\$A 20
6	\$A 50
7	\$A 100
8	\$A 40

DIP SWITCHES SETTING : 2(ccNet)

FUNCTION	SW1	SW2	SW3	SW4
Baud rate 19200	ON			
★ Baud rate 9600	OFF			
RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
★ ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT)

FUNCTION	SW1	SW2	SW3	SW4
Reserved	ON			
★ Reserved	OFF			
RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
★ ICT104U Mode		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting