

L77F&PL77-THB4

L77F&PL77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT10A/ICT104U)

Supported bill THB 20, 100, 500, 1000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / THB 20	OFF	OFF	OFF							
	2 Pulses / THB 20	OFF	OFF	ON							
	3 Pulses / THB 20	OFF	ON	OFF							
	4 Pulses / THB 20	OFF	ON	ON							
	5 Pulses / THB 20	ON	OFF	OFF							
	10 Pulses / THB 20	ON	OFF	ON							
	20 Pulses / THB 20	ON	ON	OFF							
	100 Pulses / THB 20	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept THB 20					ON					
	Reject THB 20					OFF					
★	Accept THB 100						ON				
	Reject THB 100						OFF				
★	Accept THB 500							ON			
	Reject THB 500							OFF			
★	Accept THB 1000								ON		
	Reject THB 1000								OFF		
★	High Security									ON	
	High Acceptance <small>(Note.3)</small>										OFF

★ Manufacture setting

Note:(1)Please reset the bill acceptor after any changes on Dip switch.

(2)Dip Switch 1 to 5 are only for Pulse mode.

(3)High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

L77F&PL77-THB4 (Pulse/ICT10A/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		ON	ON	
	ICT10A Mode		OFF	ON	
	Reserved		OFF	OFF	
	Power On Motor Plus				ON
★	Power On Motor Minus				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
	Reserved	ON			
★	Reserved	OFF			
★	Pulse Mode		ON	OFF	
★	ICT104U Mode		ON	ON	
	ICT10A Mode		OFF	ON	
	Reserved		OFF	OFF	
	Power On Motor Plus				ON
★	Power On Motor Minus				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse	ICT10A
BV1	THB 20	THB 20	THB 20
BV2	Reserved	Reserved	Reserved
BV3	THB 100	THB 100	THB 100
BV4	THB 500	THB 500	THB 500
BV5	THB 1000	THB 1000	THB 1000

DIP SWITCHES SETTING : 2(ICT10A)

	FUNCTION	SW1	SW2	SW3	SW4
	Reserved	ON			
★	Reserved	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		ON	ON	
★	ICT10A Mode		OFF	ON	
	Reserved		OFF	OFF	
	Power On Motor Plus				ON
★	Power On Motor Minus				OFF

★ Manufacture setting