

L77F&PL77-TRY6

L77F&PL77 DIP SWITCHES SETTING : 1(Pulse/RS232 A0/ccNet/ICT104U)

Supported bill TRY 5, 10, 20, 50, 100, 200 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / TRY 5	OFF	OFF	OFF							
2 Pulses / TRY 5	OFF	OFF	ON							
3 Pulses / TRY 5	OFF	ON	OFF							
4 Pulses / TRY 5	OFF	ON	ON							
5 Pulses / TRY 5	ON	OFF	OFF							
10 Pulses / TRY 5	ON	OFF	ON							
20 Pulses / TRY 5	ON	ON	OFF							
100 Pulses / TRY 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept TRY 5 & 10						ON				
Reject TRY 5 & 10						OFF				
★ Accept TRY 20							ON			
Reject TRY 20							OFF			
★ Accept TRY 50								ON		
Reject TRY 50								OFF		
★ Accept TRY 100									ON	
Reject TRY 100									OFF	
★ Accept TRY 200										ON
Reject TRY 200										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only for Pulse model.

Currency Assign Data

Interface Bill value	RS232 A0	Pulse	ccNet	ICT104U
BV1	TRY 5	TRY 5	TRY 5	TRY 5
BV2	TRY 10	TRY 10	TRY 10	TRY 10
BV3	TRY 20	TRY 20	TRY 20	TRY 20
BV4	TRY 50	TRY 50	TRY 50	TRY 50

Interface Bill value	RS232 A0	Pulse	ccNet	ICT104U
BV5	TRY 100	TRY 100	TRY 100	TRY 100
BV6	TRY 200	TRY 200	TRY 200	TRY 200

L77F&PL77-TRY6(Pulse/RS232 A0/ccNet/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
RS232 A0 Mode		ON	ON	
★ Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Reserved
2	Reserved
3	TRY 5
4	TRY 10
5	TRY 20
6	TRY 50
7	TRY 100
8	TRY 200
9	Reserved

DIP SWITCHES SETTING : 2(ccNet)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
9600 baud Rate	OFF			
RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
★ ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
★ ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting