

L77F/PL77-WST5

L77F/PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill WST 5, 10, 20, 50, 100 5bills.

| FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ 1 Pulse / WST 5 | OFF | OFF | OFF | | | | | | | |
| 2 Pulses / WST 5 | OFF | OFF | ON | | | | | | | |
| 3 Pulses / WST 5 | OFF | ON | OFF | | | | | | | |
| 4 Pulses / WST 5 | OFF | ON | ON | | | | | | | |
| 5 Pulses / WST 5 | ON | OFF | OFF | | | | | | | |
| 10 Pulses / WST 5 | ON | OFF | ON | | | | | | | |
| 20 Pulses / WST 5 | ON | ON | OFF | | | | | | | |
| 100 Pulses / WST 5 | ON | ON | ON | | | | | | | |
| Fast output Pulse Lo= 50ms Hi=100ms | | | | ON | | | | | | |
| ★ Slow output Pulse Lo= 50ms Hi=300ms | | | | OFF | | | | | | |
| Inhibit level Active Low | | | | | ON | | | | | |
| Inhibit level Active High | | | | | OFF | | | | | |
| ★ Accept WST 5 | | | | | | ON | | | | |
| Reject WST 5 | | | | | | OFF | | | | |
| ★ Accept WST 10 | | | | | | | ON | | | |
| Reject WST 10 | | | | | | | OFF | | | |
| ★ Accept WST 20 | | | | | | | | ON | | |
| Reject WST 20 | | | | | | | | OFF | | |
| ★ Accept WST 50 | | | | | | | | | ON | |
| Reject WST 50 | | | | | | | | | OFF | |
| ★ Accept WST 100 | | | | | | | | | | ON |
| Reject WST 100 | | | | | | | | | | OFF |

★ Manufacture setting

Note : (1) Please reset the bill acceptor after set the dip switch.
(2) Dip Switch 1 to 5 are only for Pulse mode.

L77F/PL77-WST5(Pulse/ICT104U/IC104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

| FUNCTION | SW1 | SW2 | SW3 | SW4 |
|----------------------------|-----|-----|-----|-----|
| ★ Credit-Pulse Normal HIGH | ON | | | |
| Credit-Pulse Normal LOW | OFF | | | |
| ★ Pulse Mode | | ON | OFF | |
| ICT104U Mode | | OFF | ON | |
| MDB Mode | | ON | ON | |
| ICT104V Mode | | OFF | OFF | |
| Reserved | | | | ON |
| | | | | OFF |

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

| FUNCTION | SW1 | SW2 | SW3 | SW4 |
|----------------|-----|-----|-----|-----|
| ★ Reserved | ON | | | |
| | OFF | | | |
| Pulse Mode | | ON | OFF | |
| ★ ICT104U Mode | | OFF | ON | |
| MDB Mode | | ON | ON | |
| ICT104V Mode | | OFF | OFF | |
| Reserved | | | | ON |
| | | | | OFF |

★ Manufacture setting

Currency Assign Data

| Interface Bill value | Pulse | MDB | ICT104U | ICT104V |
|-------------------------|---------|---------|---------|---------|
| BV1 | WST 5 | WST 5 | WST 5 | WST 5 |
| BV2 | WST 10 | WST 10 | WST 10 | WST 10 |
| BV3 | WST 20 | WST 20 | WST 20 | WST 20 |
| BV4 | WST 50 | WST 50 | WST 50 | WST 50 |
| BV5 | WST 100 | WST 100 | WST 100 | WST 100 |

DIP SWITCHES SETTING : 2(ICT104V)

| FUNCTION | SW1 | SW2 | SW3 | SW4 |
|----------------|-----|-----|-----|-----|
| ★ Reserved | ON | | | |
| | OFF | | | |
| Pulse Mode | | ON | OFF | |
| ICT104U Mode | | OFF | ON | |
| MDB Mode | | ON | ON | |
| ★ ICT104V Mode | | OFF | OFF | |
| Reserved | | | | ON |
| | | | | OFF |

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

| FUNCTION | SW1 | SW2 | SW3 | SW4 |
|---|-----|-----|-----|-----|
| ★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2 | ON | | | |
| Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0 | OFF | | | |
| Pulse Mode | | ON | OFF | |
| ICT104U Mode | | OFF | ON | |
| ★ MDB Mode | | ON | ON | |
| ICT104V Mode | | OFF | OFF | |
| Reserved | | | | ON |
| | | | | OFF |

★ Manufacture setting