

# L77F&PL77-UAH10

## L77F&PL77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB)

Supported bill HRYVEN 1, 2, 5, 10, 20, 50, 100, 200, 500, 1000 10bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / HRYVEN 1 & 5 (Note.3)	OFF	OFF	OFF							
2 Pulse / HRYVEN 1 & 5 (Note.3)	OFF	OFF	ON							
3 Pulse / HRYVEN 1 & 5 (Note.3)	OFF	ON	OFF							
4 Pulse / HRYVEN 1 & 5 (Note.3)	OFF	ON	ON							
5 Pulse / HRYVEN 1 & 5 (Note.3)	ON	OFF	OFF							
10 Pulse / HRYVEN 1 & 5 (Note.3)	ON	OFF	ON							
20 Pulse / HRYVEN 1 & 5 (Note.3)	ON	ON	OFF							
100 Pulse / HRYVEN 1 & 5 (Note.3)	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept HRYVEN 1 & 2 (Note.3)						ON				
Reject HRYVEN 1 & 2 (Note.3)						OFF				
★ Accept HRYVEN 5 & 10							ON			
Reject HRYVEN 5 & 10							OFF			
★ Accept HRYVEN 20 & 50								ON		
Reject HRYVEN 20 & 50								OFF		
★ Accept HRYVEN 100 & 200									ON	
Reject HRYVEN 100 & 200									OFF	
★ Accept HRYVEN 500 & 1000										ON
Reject HRYVEN 500 & 1000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only for Pulse mode.

(3) Pulse Mode:

Dip 6 turn ON, One Pulse per HRYVEN 1.

Dip 6 turn OFF, One Pulse per HRYVEN 5.

MDB Mode:

Dip 6 turn ON (MDB Protocol:Reject UAH 500,UAH 1000)

Dip 6 turn OFF (MDB Protocol:Accept UAH 500,UAH 1000)

# L77F&PL77-UAH9(Pulse/ICT104U/MDB)

## DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
Reserved		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
Reserved		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
Reserved		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	ICT104U	Pulse		MDB	
		Dip 6 is ON	Dip 6 is OFF	Dip 6 is ON	Dip 6 is OFF
BV1	HRYPVEN 1	HRYPVEN 1	HRYPVEN 5	HRYPVEN 1	HRYPVEN 5
BV2	HRYPVEN 2	HRYPVEN 2	HRYPVEN 10	HRYPVEN 2	HRYPVEN 10
BV3	HRYPVEN 5	HRYPVEN 5	HRYPVEN 20	HRYPVEN 5	HRYPVEN 20
BV4	HRYPVEN 10	HRYPVEN 10	HRYPVEN 50	HRYPVEN 10	HRYPVEN 50
BV5	HRYPVEN 20	HRYPVEN 20	HRYPVEN 100	HRYPVEN 20	HRYPVEN 100
BV6	HRYPVEN 50	HRYPVEN 50	HRYPVEN 200	HRYPVEN 50	HRYPVEN 200
BV7	HRYPVEN 100	HRYPVEN 100	HRYPVEN 500	HRYPVEN 100	HRYPVEN 500
BV8	HRYPVEN 200	HRYPVEN 200	HRYPVEN 1000	HRYPVEN 200	HRYPVEN 1000
BV9	HRYPVEN 500	HRYPVEN 500			
BV10	HRYPVEN 1000	HRYPVEN 1000			