

L83-MGA5

L83 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill MGA 500, 1000, 2000, 5000, 10000 5 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / MGA 500	OFF	OFF	OFF							
	2 Pulses / MGA 500	OFF	OFF	ON							
	3 Pulses / MGA 500	OFF	ON	OFF							
	4 Pulses / MGA 500	OFF	ON	ON							
	5 Pulses / MGA 500	ON	OFF	OFF							
	10 Pulses / MGA 500	ON	OFF	ON							
	20 Pulses / MGA 500	ON	ON	OFF							
	100 Pulses / MGA 500	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept MGA 500				ON						
	Reject MGA 500				OFF						
★	Accept MGA 1000				ON						
	Reject MGA 1000				OFF						
★	Accept MGA 2000				ON						
	Reject MGA 2000				OFF						
★	Accept MGA 5000				ON						
	Reject MGA 5000				OFF						
★	Accept MGA 10000				ON						
	Reject MGA 10000				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L83-MGA5(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	MGA 500	MGA 500	MGA 500	MGA 500
BV2	MGA 1000	MGA 1000	MGA 1000	MGA 1000
BV3	MGA 2000	MGA 2000	MGA 2000	MGA 2000
BV4	MGA 5000	MGA 5000	MGA 5000	MGA 5000
BV5	MGA 10000	MGA 10000	MGA 10000	MGA 10000

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
★	ICT104V Mode		OFF	OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	ON			
	Scaling Factor (SF) = 10 Decimal Point Position (DPP) = 1	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
★	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting