

V7P-AED6

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill AED 5, 10, 20, 50, 100, 200 6bills.

V7P dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject AED 5 & 10	ON											
★ Accept AED 5 & 10	OFF											
★ Reject AED 20		ON										
★ Accept AED 20		OFF										
★ Reject AED 50			ON									
★ Accept AED 50			OFF									
★ Reject AED 100				ON								
★ Accept AED 100				OFF								
★ Reject AED 200					ON							
★ Accept AED 200					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ Pulse Mode												
★ 1 pulse / AED 5								OFF	OFF			
5 pulses / AED 5								ON	OFF			
10 pulses / AED 5								OFF	ON			
25 pulses / AED 5								ON	ON			
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note :

- 1.Default setting.
- 2.Use 2nd and 3rd dip of the internal dip-switch to change different interface Protocol.
- 3.Remove the front cover and the dip-switch in on the CPU board.

V7P-AED6(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Bill value	Pulse	MDB	ICT104V	ICT104U
BV1	AED 5	AED 5	AED 5	AED 5
BV2	AED 10	AED 10	AED 10	AED 10
BV3	AED 20	AED 20	AED 20	AED 20
BV4	AED 50	AED 50	AED 50	AED 50
BV5	AED 100	AED 100	AED 100	AED 100
BV6	AED 200	AED 200	AED 200	AED 200

Interface Settings: 2(ICT104U/ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	ON	ON	OFF	
	OFF	OFF	OFF	
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting