

# V7P-EGP4

## V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

### Supported bill EGP 5, 10, 20, 50 4bills.

V7P dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject EGP 5	ON											
★ Accept EGP 5	OFF											
★ Reject EGP 10		ON										
★ Accept EGP 10		OFF										
★ Reject EGP 20			ON									
★ Accept EGP 20			OFF									
★ Reject EGP 50				ON								
★ Accept EGP 50				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ <b>Pulse Mode</b>												
★ 1 pulse / EGP 5								OFF	OFF			
★ 2 pulses / EGP 5								ON	OFF			
★ 5 pulses / EGP 5								OFF	ON			
★ 20 pulses / EGP 5								ON	ON			
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note :

- 1.Default setting.
- 2.Use 2nd and 3rd dip of the internal dip-switch to change different interface Protocol.
- 3.Remove the front cover and the dip-switch in on the CPU board.

# V7P-EGP4(Pulse/ICT104V/ICT104U/MDB)

## Interface Settings: 2(Pulse) Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface	Pulse	MDB	ICT104V	ICT104U
★ Bill value				
BV1	EGP 5	EGP 5	EGP 5	EGP 5
BV2	EGP 10	EGP 10	EGP 10	EGP 10
BV3	EGP 20	EGP 20	EGP 20	EGP 20
BV4	EGP 50	EGP 50	EGP 50	EGP 50

## Interface Settings: 2(ICT104U/ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

## Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting