

V7P-SEK4

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill SKr 20, 50, 100, 200 4bills.

V7P dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject SKr 20	ON											
★ Accept SKr 20	OFF											
★ Reject SKr 50		ON										
★ Accept SKr 50		OFF										
★ Reject SKr 100			ON									
★ Accept SKr 100			OFF									
★ Reject SKr 200				ON								
★ Accept SKr 200				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / SKr 10									OFF	OFF		
★ 5 pulses / SKr 10									ON	OFF		
★ 10 pulses / SKr 10									OFF	ON		
★ 25 pulses / SKr 10									ON	ON		
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

V7P-SEK4(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
★ Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
★ ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
	BV1	SKr 20	SKr 20	SKr 20
BV2	SKr 50	SKr 50	SKr 50	SKr 50
BV3	SKr 100	SKr 100	SKr 100	SKr 100
BV4	SKr 200	SKr 200	SKr 200	SKr 200

Interface Settings: 2(ICT104U/ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
★ Reserved	OFF			
★ Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
★ ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
★ Reserved	OFF			
★ Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
★ ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
★ Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★ Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
★ ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting