

A6 PLUS-ARA6

A6 PLUS Option Switch Settings: 1(Pulse/ID003)

Supported bill \$ 2(97), 5(98), 10(98), 20(00), 50(99), 100(99)
6 bills.

A6 PLUS dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject \$ 2 & 5	ON											
★	Accept \$ 2 & 5	OFF											
★	Reject \$ 10		ON										
★	Accept \$ 10		OFF										
★	Reject \$ 20			ON									
★	Accept \$ 20			OFF									
★	Reject \$ 50				ON								
★	Accept \$ 50				OFF								
★	Reject \$ 100					ON							
★	Accept \$ 100					OFF							
★	High Acceptance						ON						
★	High Security						OFF						
★	Harness Disable							ON					
★	Harness Enable							OFF					
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / \$ 1									OFF	OFF		
	2 pulse / \$ 1									ON	OFF		
	4 pulse / \$ 1									OFF	ON		
	20 pulse / \$ 1									ON	ON		
★	Interface Timing Conversion	50ms on / 50ms off								OFF	OFF		
		60ms on / 300ms off								ON	OFF		
		30ms on / 50ms off								OFF	ON		
		150ms on / 150ms off								ON	ON		

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A6 PLUS-ARA6

A6 PLUS Interface Settings: 2(Pulse/ID003)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
	Pulse Mode		ON		
★	ID003 Protocol Mode		OFF		
	HOLD			ON	
				OFF	
					ON
					OFF

★ Manufacture setting