

**A6/V6 Option Switch Settings**

Supported bill R\$ 1(94, 03), 2(01), 5(94), 10(94, 00), 20(02), 50(94)

A6/V6 dip-switch settings and functions:

**6bills.**

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
Reject R\$ 1	ON											
Accept R\$ 1	OFF											
Reject R\$ 2		ON										
Accept R\$ 2		OFF										
Reject R\$ 5			ON									
Accept R\$ 5			OFF									
Reject R\$ 10				ON								
Accept R\$ 10				OFF								
Reject R\$ 20 & 50					ON							
Accept R\$ 20 & 50					OFF							
High Acceptance						ON						
High Security						OFF						
Harness disable							ON					
Harness enable							OFF					
Inhibit Active High								ON				
Inhibit Active Low								OFF				
★ 1 pulse / R\$ 1									OFF	OFF		
★ 2 pulse / R\$ 1									ON	OFF		
4 pulse / R\$ 1									OFF	ON		
20 pulse / R\$ 1									ON	ON		
★ Interface Timing Conversion		50ms on / 50ms off									OFF	OFF
		60ms on / 300ms off									ON	OFF
		30ms on / 50ms off									OFF	ON
		150ms on / 150ms off									ON	ON

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

## **A6 Interface Settings: 2**

	INTERFACE	SW1	SW2	SW3	SW4	
★	Credit-Pulse Normal HIGH	ON				
	Credit-Pulse Normal LOW	OFF				
	Pulse Mode		ON			
★	RS232 Interface		OFF			
	<b>HOLD</b>			ON		
				OFF		
					ON	
					OFF	

## **V6 Interface Settings: 3**

	INTERFACE	SW1	SW2	SW3	SW4	
★	Credit-Pulse Normal HIGH	ON				
	Credit-Pulse Normal LOW	OFF				
	Pulse Mode		ON			
★	MDB Interface		OFF			
	<b>HOLD</b>			ON		
				OFF		
					ON	
					OFF	