

A7/V7 Option Switch Settings : 1(Pulse/Parallel)

Supported bill Euro 5, 10, 20 3bills.

A7/V7 dip-switch settings and functions:

| FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 |
|-----------------------|----------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| ★ Reject Euro 5 | ON | | | | | | | | | | | |
| ★ Accept Euro 5 | OFF | | | | | | | | | | | |
| ★ Reject Euro 10 | | ON | | | | | | | | | | |
| ★ Accept Euro 10 | | OFF | | | | | | | | | | |
| ★ Reject Euro 20 | | | ON | | | | | | | | | |
| ★ Accept Euro 20 | | | OFF | | | | | | | | | |
| ★ Reserved | | | | ON | | | | | | | | |
| ★ Reserved | | | | OFF | | | | | | | | |
| ★ Reserved | | | | | ON | | | | | | | |
| ★ Reserved | | | | | OFF | | | | | | | |
| ★ Reserved | | | | | | ON | | | | | | |
| ★ Reserved | | | | | | OFF | | | | | | |
| ★ Harness Disable | | | | | | | ON | | | | | |
| ★ Harness Enable | | | | | | | OFF | | | | | |
| ★ Inhibit Active High | | | | | | | | ON | | | | |
| ★ Inhibit Active Low | | | | | | | | OFF | | | | |
| ★ 1 pulse / Euro 5 | | | | | | | | | OFF | OFF | | |
| ★ 5 pulse / Euro 5 | | | | | | | | | ON | OFF | | |
| ★ 10 pulse / Euro 5 | | | | | | | | | OFF | ON | | |
| ★ 20 pulse / Euro 5 | | | | | | | | | ON | ON | | |
| ★ Pulse Speed | 50ms on / 50ms off | | | | | | | | OFF | OFF | | |
| | 60ms on / 300ms off | | | | | | | | ON | OFF | | |
| | 30ms on / 50ms off | | | | | | | | OFF | ON | | |
| | 150ms on / 150ms off | | | | | | | | ON | ON | | |

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW6 . SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

Interface Settings: 2(Pulse)

| INTERFACE | SW1 | SW2 | SW3 | SW4 |
|----------------------------|-----|-----|-----|-----|
| ★ Credit-Pulse Normal HIGH | ON | | | |
| Credit-Pulse Normal LOW | OFF | | | |
| ★ Pulse Mode | | ON | | |
| Parallel Interface | | OFF | | |
| ★ Reserved | | | ON | |
| | | | OFF | |
| | | | | ON |
| | | | | OFF |

★ Manufacture setting

Interface Settings : 3(Parallel)

| INTERFACE | SW1 | SW2 | SW3 | SW4 |
|----------------------|-----|-----|-----|-----|
| ★ Reserved | ON | | | |
| | OFF | | | |
| Pulse Mode | | ON | | |
| ★ Parallel Interface | | OFF | | |
| ★ Reserved | | | ON | |
| | | | OFF | |
| | | | | ON |
| | | | | OFF |

★ Manufacture setting

