

A7/V7-BAM3

A7/V7 Option Switch Settings : 1(Pulse/Parallel)

Supported bill MARAKA 10, 20, 50 3bills.

A7/V7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject MARAKA 10	ON											
★ Accept MARAKA 10	OFF											
★ Reject MARAKA 20		ON										
★ Accept MARAKA 20		OFF										
★ Reject MARAKA 50			ON									
★ Accept MARAKA 50			OFF									
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / MARAKA 10									OFF	OFF		
5 pulse / MARAKA 10									ON	OFF		
10 pulse / MARAKA 10									OFF	ON		
20 pulse / MARAKA 10									ON	ON		
★ Pulse Speed		50ms on / 50ms off									OFF	OFF
		60ms on / 300ms off									ON	OFF
		30ms on / 50ms off									OFF	ON
		150ms on / 150ms off									ON	ON

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW6 . SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A7/V7-BAM3

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
Parallel Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

Interface Settings : 3(Parallel)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON		
Parallel Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting