

A7/V7-RSD7

A7/V7 Option Switch Settings : 1(Pulse/Parallel)

Supported bill RSD 10, 20, 50, 100, 200, 500, 1000

7bills.

A7/V7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject RSD 10 & 20	ON											
★ Accept RSD 10 & 20	OFF											
★ Reject RSD 50 & 100		ON										
★ Accept RSD 50 & 100		OFF										
★ Reject RSD 200			ON									
★ Accept RSD 200			OFF									
★ Reject RSD 500				ON								
★ Accept RSD 500				OFF								
★ Reject RSD 1000					ON							
★ Accept RSD 1000					OFF							
★ High Acceptance						ON						
★ High Security						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / RSD 10									OFF	OFF		
5 pulse / RSD 10									ON	OFF		
10 pulse / RSD 10									OFF	ON		
25 pulse / RSD 10									ON	ON		
★ Pulse Speed	50ms on / 50ms off								OFF	OFF		
	60ms on / 300ms off								ON	OFF		
	30ms on / 50ms off								OFF	ON		
	150ms on / 150ms off								ON	ON		

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW6 . SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A7/V7-RSD7

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
Parallel Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

Interface Settings : 3(Parallel)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON		
Parallel Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting