



HUF7

L70/P5 DIP SWITCHES SETTING : 1(ICT/ccTalk)

Supported bill Ft 200, 500, 1000, 2000, 5000,
10000, 20000 7bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ ★ ★ ★ ★ ★ ★ ★ ★ ★ Reserved	ON									
	OFF									
		ON								
		OFF								
			ON							
			OFF							
				ON						
				OFF						
					ON					
					OFF					
★ Accept Ft 200 & 500						ON				
★ Reject Ft 200 & 500						OFF				
★ Accept Ft 1000 & 2000							ON			
★ Reject Ft 1000 & 2000							OFF			
★ Accept Ft 5000								ON		
★ Reject Ft 5000								OFF		
★ Accept Ft 10000									ON	
★ Reject Ft 10000									OFF	
★ Accept Ft 20000										ON
★ Reject Ft 20000										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2(ICT)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	ICT Protocol		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	ccTalk Interface		OFF	OFF	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.