

L70/L70F-IDR7

L70/L70F-P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill Rp 1000, 2000, 5000, 10000, 20000, 50000, 100000 7bills.

| FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ 1 Pulse / Rp 1000 | OFF | OFF | OFF | | | | | | | |
| 2 Pulse / Rp 1000 | OFF | OFF | ON | | | | | | | |
| 3 Pulse / Rp 1000 | OFF | ON | OFF | | | | | | | |
| 4 Pulse / Rp 1000 | OFF | ON | ON | | | | | | | |
| 5 Pulse / Rp 1000 | ON | OFF | OFF | | | | | | | |
| 10 Pulse / Rp 1000 | ON | OFF | ON | | | | | | | |
| 20 Pulse / Rp 1000 | ON | ON | OFF | | | | | | | |
| 100 Pulse / Rp 1000 | ON | ON | ON | | | | | | | |
| ★ Fast output Pulse Lo= 50ms Hi=100ms | | | | ON | | | | | | |
| ★ Slow output Pulse Lo= 50ms Hi=300ms | | | | OFF | | | | | | |
| ★ Inhibit level Active Low | | | | | ON | | | | | |
| ★ Inhibit level Active High | | | | | OFF | | | | | |
| ★ Accept Rp 1000 | | | | | | ON | | | | |
| Reject Rp 1000 | | | | | | OFF | | | | |
| ★ Accept Rp 2000 & 5000 & 10000 & 20000 | | | | | | | ON | | | |
| Reject Rp 2000 & 5000 & 10000 & 20000 | | | | | | | OFF | | | |
| ★ Accept Rp 50000 | | | | | | | | ON | | |
| Reject Rp 50000 | | | | | | | | OFF | | |
| ★ Accept Rp 100000 | | | | | | | | | ON | |
| Reject Rp 100000 | | | | | | | | | OFF | |
| ★ High Security | | | | | | | | | | ON |
| High Acceptance (Note.3) | | | | | | | | | | OFF |

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

(4) The function(credit divide by1000) is only used at standard MDB recycler mode.

(5) i.Special MDB setting mode works for vending machine. It can't accept IDR 100,000 bill in this mode.

ii.The function(Normal credit/Credit divide) is disable when BA works at special MDB Setting Mode.

L70/L70F-IDR7(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

| FUNCTION | SW1 | SW2 | SW3 | SW4 |
|---------------------|-----|-----|-----|-----|
| ★ Pulse Normal High | ON | | | |
| Pulse Normal Low | OFF | | | |
| ★ Pulse Mode | | ON | OFF | |
| ICT104U Mode | | OFF | ON | |
| MDB Mode | | ON | ON | |
| ICT104V Mode | | OFF | OFF | |
| ★ Reserved | | | | ON |
| | | | | OFF |

★ Manufacture setting

Currency Assign Data

| Interface Bill value | MDB | Pulse | ICT104U | ICT104V |
|----------------------|-----------|-----------|-----------|-----------|
| BV1 | Rp 1000 | Rp 1000 | Rp 1000 | Rp 1000 |
| BV2 | Rp 2000 | Rp 2000 | Rp 2000 | Rp 2000 |
| BV3 | Rp 5000 | Rp 5000 | Rp 5000 | Rp 5000 |
| BV4 | Rp 10000 | Rp 10000 | Rp 10000 | Rp 10000 |
| BV5 | Rp 20000 | Rp 20000 | Rp 20000 | Rp 20000 |
| BV6 | Rp 50000 | Rp 50000 | Rp 50000 | Rp 50000 |
| BV7 | Rp 100000 | Rp 100000 | Rp 100000 | Rp 100000 |

DIP SWITCHES SETTING : 2(ICT104U)

| FUNCTION | SW1 | SW2 | SW3 | SW4 |
|----------------|-----|-----|-----|-----|
| ★ Reserved | ON | | | |
| | OFF | | | |
| Pulse Mode | | ON | OFF | |
| ★ ICT104U Mode | | OFF | ON | |
| MDB Mode | | ON | ON | |
| ICT104V Mode | | OFF | OFF | |
| ★ Reserved | | | | ON |
| | | | | OFF |

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

| FUNCTION | SW1 | SW2 | SW3 | SW4 |
|----------------|-----|-----|-----|-----|
| ★ Reserved | ON | | | |
| | OFF | | | |
| Pulse Mode | | ON | OFF | |
| ★ ICT104U Mode | | OFF | ON | |
| MDB Mode | | ON | ON | |
| ★ ICT104V Mode | | OFF | OFF | |
| ★ Reserved | | | | ON |
| | | | | OFF |

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

| FUNCTION | SW1 | SW2 | SW3 | SW4 |
|--|-----|-----|-----|-----|
| ★ Normal credit | ON | | | |
| Credit divide by 1000(MDB only) (Note.4) | OFF | | | |
| Pulse Mode | | ON | OFF | |
| ★ ICT104U Mode | | OFF | ON | |
| MDB Mode | | ON | ON | |
| ICT104V Mode | | OFF | OFF | |
| Special MDB Setting(Base 5) (Note.5) | | | | ON |
| ★ Normal MDB Setting | | | | OFF |

★ Manufacture setting