

VND7

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill VND 5000, 10000, 20000, 50000, 100000, 200000, 500000 7bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / VND 5000	OFF	OFF	OFF							
2 Pulse / VND 5000	OFF	OFF	ON							
3 Pulse / VND 5000	OFF	ON	OFF							
4 Pulse / VND 5000	OFF	ON	ON							
5 Pulse / VND 5000	ON	OFF	OFF							
10 Pulse / VND 5000	ON	OFF	ON							
20 Pulse / VND 5000	ON	ON	OFF							
100 Pulse / VND 5000	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept VND 5000						ON				
Reject VND 5000						OFF				
★ Accept VND 10000							ON			
Reject VND 10000							OFF			
★ Accept VND 20000								ON		
Reject VND 20000								OFF		
★ Accept VND 50000									ON	
Reject VND 50000									OFF	
★ Accept VND 100000 & 200000 & 500000										ON
Reject VND 100000 & 200000 & 500000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70-VND7/P5(Pulse/ICT)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON		
ICT Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
★ ICT Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
★				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	VND 5000	VND 5000
BV2	VND 10000	VND 10000
BV3	VND 20000	VND 20000
BV4	VND 50000	VND 50000
BV5	VND 100000	VND 100000
BV6	VND 200000	VND 200000
BV7	VND 500000	VND 500000