

## L70/L70F-AOA3

### L70/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill AOA 200, 500, 1000 3bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / AOA 100	OFF	OFF	OFF							
	2 Pulses / AOA 100	OFF	OFF	ON							
	3 Pulses / AOA 100	OFF	ON	OFF							
	4 Pulses / AOA 100	OFF	ON	ON							
	5 Pulses / AOA 100	ON	OFF	OFF							
	10 Pulses / AOA 100	ON	OFF	ON							
	20 Pulses / AOA 100	ON	ON	OFF							
	100 Pulses / AOA 100	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept AOA 200					ON					
	Reject AOA 200					OFF					
★	Accept AOA 500						ON				
	Reject AOA 500						OFF				
★	Accept AOA 1000							ON			
	Reject AOA 1000							OFF			
★	Reserved								ON		
	Reserved								OFF		
★	Reserved									ON	
	Reserved									OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## L70/L70F-AOA3(Pulse/ICT104U/ICT104V/MDB)

### DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
★	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	AOA 200	AOA 200	AOA 200	AOA 200
BV2	AOA 500	AOA 500	AOA 500	AOA 500
BV3	AOA 1000	AOA 1000	AOA 1000	AOA 1000

### DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
★	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting