

L70+/L70F-HNL6

L70+/L70F DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill HNL 10, 20, 50, 100, 200, 500 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / HNL 10	OFF	OFF	OFF							
2 Pulses / HNL 10	OFF	OFF	ON							
3 Pulses / HNL 10	OFF	ON	OFF							
4 Pulses / HNL 10	OFF	ON	ON							
5 Pulses / HNL 10	ON	OFF	OFF							
10 Pulses / HNL 10	ON	OFF	ON							
20 Pulses / HNL 10	ON	ON	OFF							
100 Pulses / HNL 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept HNL 10						ON				
Reject HNL 10						OFF				
★ Accept HNL 20							ON			
Reject HNL 20							OFF			
★ Accept HNL 50								ON		
Reject HNL 50								OFF		
★ Accept HNL 100 & 200									ON	
Reject HNL 100 & 200									OFF	
★ Accept HNL 500										ON
Reject HNL 500										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70+/L70F-HNL6(Pulse/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Protocol		ON		
ICT104U Protocol		OFF		
Reserved			ON	
★ Reserved			OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Protocol		ON		
★ ICT104U Protocol		OFF		
Reserved			ON	
★ Reserved			OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U
BV1		
BV2	HNL 10	HNL 10
BV3	HNL 20	HNL 20
BV4	HNL 50	HNL 50
BV5	HNL 100	HNL 100
BV6	HNL 200	HNL 200
BV7	HNL 500	HNL 500