

## V7E/LX7-OMR2

### V7E/LX7 Option Switch Settings: 1(Pulse/ICT104U/M.D.B)

### Supported bill OMR 0.1, 0.5 2bills.

V7E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject OMR 0.1	ON											
★	Accept OMR 0.1	OFF											
★	Reject OMR 0.5		ON										
★	Accept OMR 0.5		OFF										
★	Reserved			ON									
★	Reserved			OFF									
★	Reserved			ON									
★	Reserved			OFF									
★	Reserved				ON								
★	Reserved				OFF								
★	Reserved					ON							
★	Reserved					OFF							
★	<b>Pulse Mode</b>	<b>Other Mode</b>											
★	Harness Disable	BA stops working when fishing						ON					
★	Harness Enable	Normal						OFF					
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / OMR 0.1							OFF	OFF				
★	5 pulses / OMR 0.1							ON	OFF				
★	10 pulses / OMR 0.1							OFF	ON				
★	25 pulses / OMR 0.1							ON	ON				
★	Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) Use both 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

## V7E/LX7-OMR2(Pulse/ICT104U/M.D.B)

### DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 3	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 1	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
★	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	ICT104U	Pulse	MDB
BV1	OMR 0.1	OMR 0.1	OMR 0.1
BV2	OMR 0.5	OMR 0.5	OMR 0.5