



BEM8

P77/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill BAM 5(98-1,98-2), 10(98-1,98-2), 20(98-1,98-2), 50(98-1,98-2)
 EUR 5(02), 10(02), 20(02), 50(02) 8bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
* 1 Pulse / MARAKA 5	OFF	OFF	OFF							
2 Pulse / MARAKA 5	OFF	OFF	ON							
3 Pulse / MARAKA 5	OFF	ON	OFF							
4 Pulse / MARAKA 5	OFF	ON	ON							
5 Pulse / MARAKA 5	ON	OFF	OFF							
10 Pulse / MARAKA 5	ON	OFF	ON							
20 Pulse / MARAKA 5	ON	ON	OFF							
100 Pulse / MARAKA 5	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
* Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
* Inhibit level Active High					OFF					
* Accept MARAKA 5 & 10 & Euro 5						ON				
Reject MARAKA 5 & 10 & Euro 5						OFF				
* Accept MARAKA 20 & Euro 10							ON			
Reject MARAKA 20 & Euro 10							OFF			
* Accept Euro 20								ON		
Reject Euro 20								OFF		
* Accept MARAKA 50									ON	
Reject MARAKA 50									OFF	
* Accept Euro 50										ON
Reject Euro 50										OFF

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.
 (2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
* Pulse Normal High	ON			
Pulse Normal Low	OFF			
* Pulse Protocol		ON		
ICT Protocol		OFF		
Harness Disable			ON	
* Harness Enable			OFF	
Ignore Sensor Problem(Note 1)				ON
* Acknowledge Sensor Problem (Note 2)				OFF

★ Manufacture setting

Note : (1) Sensor 6 problem occurred ==>> BA will be still in working order.
 (The face LED will be flashing in short green about 2 seconds everytime you restart BA.)
 (2) BA will stop to work when it acknowledges Sensor 6 problem occurred.
 (The face LED will be flashing in red.)