



# PKR7

## P77/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill Prs 10(old, 06), 20(05), 50, 100(old, 06),  
500(old, 06), 1000, 5000(06) 7 bills.

Note: 500(old), 1000 is not taken by P77/P5.

| FUNCTION  | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ 1 Pulse / PRs 10  | OFF | OFF | OFF |     |     |     |     |     |     |      |
| 2 Pulse / PRs 10  | OFF | OFF | ON  |     |     |     |     |     |     |      |
| 3 Pulse / PRs 10  | OFF | ON  | OFF |     |     |     |     |     |     |      |
| 4 Pulse / PRs 10  | OFF | ON  | ON  |     |     |     |     |     |     |      |
| 5 Pulse / PRs 10  | ON  | OFF | OFF |     |     |     |     |     |     |      |
| 10 Pulse / PRs 10   | ON  | OFF | ON  |     |     |     |     |     |     |      |
| 20 Pulse / PRs 10   | ON  | ON  | OFF |     |     |     |     |     |     |      |
| 100 Pulse / PRs 10  | ON  | ON  | ON  |     |     |     |     |     |     |      |
| Fast output Pulse<br><small>Lo= 50ms<br/>Hi=100ms</small>   |     |     |     | ON  |     |     |     |     |     |      |
| ★ Slow output Pulse<br><small>Lo= 50ms<br/>Hi=300ms</small> |     |     |     | OFF |     |     |     |     |     |      |
| Inhibit level Active Low                                    |     |     |     |     | ON  |     |     |     |     |      |
| ★ Inhibit level Active High                                 |     |     |     |     | OFF |     |     |     |     |      |
| ★ Accept PRs 10 & 20  |     |     |     |     |     | ON  |     |     |     |      |
| Reject PRs 10 & 20  |     |     |     |     |     | OFF |     |     |     |      |
| ★ Accept PRs 50 & 100                                       |     |     |     |     |     |     | ON  |     |     |      |
| Reject PRs 50 & 100   |     |     |     |     |     |     | OFF |     |     |      |
| ★ Accept PRs 500  |     |     |     |     |     |     |     | ON  |     |      |
| Reject PRs 500  |     |     |     |     |     |     |     | OFF |     |      |
| ★ Accept PRs 1000   |     |     |     |     |     |     |     |     | ON  |      |
| Reject PRs 1000   |     |     |     |     |     |     |     |     | OFF |      |
| ★ Accept PRs 5000   |     |     |     |     |     |     |     |     |     | ON   |
| Reject PRs 5000   |     |     |     |     |     |     |     |     |     | OFF  |

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.  
(2)Dip switches 1 to 5 are only used for pulse protocol.

## DIP SWITCHES SETTING : 2

| FUNCTION                              | SW1 | SW2 | SW3 | SW4 |
|---------------------------------------|-----|-----|-----|-----|
| ★ Pulse Normal High                   | ON  |     |     |     |
| Pulse Normal Low                      | OFF |     |     |     |
| Pulse Protocol                        |     | ON  |     |     |
| ICT Protocol                          |     | OFF |     |     |
| Harness Disable                       |     |     | ON  |     |
| ★ Harness Enable                      |     |     | OFF |     |
| Ignore Sensor Problem(Note 1)         |     |     |     | ON  |
| ★ Acknowledge Sensor Problem (Note 2) |     |     |     | OFF |

★ Manufacture setting

Note : (1) Sensor 6 problem occurred ==>> BA will be still in working order.  
(The face LED will be flashing in short green about 2 seconds everytime you restart BA.)  
(2) BA will stop to work when it acknowledges Sensor 6 problem occurred.  
(The face LED will be flashing in red.)