

TAO-A/V Option Switch Settings: 1

Supported bill \$ 2, 5, 10, 20, 50, 100 6bills.

TAO-A/V dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject \$ 2 & 5	ON											
★	Accept \$ 2 & 5	OFF											
	Reject \$ 10		ON										
★	Accept \$ 10		OFF										
	Reject \$ 20			ON									
★	Accept \$ 20			OFF									
	Reject \$ 50				ON								
★	Accept \$ 50				OFF								
	Reject \$ 100					ON							
★	Accept \$ 100					OFF							
	Reserved						ON						
★	Reserved						OFF						
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / \$ 1									OFF	OFF		
	2 pulse / \$ 1									ON	OFF		
	4 pulse / \$ 1									OFF	ON		
	20 pulse / \$ 1									ON	ON		
★	Interface Timing Conversion	50ms on / 50ms off										OFF	OFF
		60ms on / 300ms off										ON	OFF
		30ms on / 50ms off										OFF	ON
		150ms on / 150ms off										ON	ON

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A TYPE Interface Settings: 2(Pulse/RS232)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	RS232 Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
					OFF

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON		
★	RS232 Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
					OFF

★ Manufacture setting

V TYPE Interface Settings: 2(Pulse/M.D.B)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	M.D.B Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
					OFF

★ Manufacture setting

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	M.D.B Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
					OFF

★ Manufacture setting