

TAO-A.V-AUD4

TAO-A.V Option Switch Settings: 1(Pulse/ICT104V/ICT104U/ MDB)

Supported bill \$A 5, 10, 20
Blue, Orange

3 Bills.
2 Coupon.

TAO-V dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject \$A 5	ON											
★ Accept \$A 5	OFF											
★ Reject \$A 10		ON										
★ Accept \$A 10		OFF										
★ Reject \$A 20			ON									
★ Accept \$A 20			OFF									
★ Reject Blue mei-coupon				ON								
★ Accept Blue mei-coupon				OFF								
★ Reject Orange mei-coupon					ON							
★ Accept Orange mei-coupon					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / \$A 5									OFF	OFF		
5 pulses / \$A 5									ON	OFF		
10 pulses / \$A 5									OFF	ON		
20 pulses / \$A 5									ON	ON		
★ Interface Timing Conversion	50ms LO / 50ms HI										OFF	OFF
	60ms LO / 300ms HI										ON	OFF
	30ms LO / 50ms HI										OFF	ON
	150ms LO / 150ms HI										ON	ON

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "Sw1" setting.)

BV1=\$A 5,BV2=\$A 10,BV3=\$A 20,BV4=Blue mei-coupon,BV5=Orange mei-coupon.

TAO-A.V-AUD4(Pulse/ICT104V/ICT104U/ MDB)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104V	ICT104U	Pulse	MDB
BV1	\$A 5	\$A 5	\$A 5	\$A 5
BV2	\$A 10	\$A 10	\$A 10	\$A 10
BV3	\$A 20	\$A 20	\$A 20	\$A 20
BV4	Blue mei-coupon	Blue mei-coupon	Blue mei-coupon	Blue mei-coupon (FREE VEND)
BV5	Orange mei-coupon	Orange mei-coupon	Orange mei-coupon	Orange mei-coupon (FREE VEND)

Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

TAO-V-AUD4

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting