

TAO-A/V Option Switch Settings: 1

Supported bill Pesos 20, 50, 100, 200 4bills.

TAO-A/V dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject Pesos 20	ON											
★	Accept Pesos 20	OFF											
	Reject Pesos 50		ON										
★	Accept Pesos 50		OFF										
	Reject Pesos 100			ON									
★	Accept Pesos 100			OFF									
	Reject Pesos 200				ON								
★	Accept Pesos 200				OFF								
	Reserved					ON							
★	Reserved					OFF							
	Reserved						ON						
★	Reserved						OFF						
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / Pesos 10									OFF	OFF		
	2 pulse / Pesos 10									ON	OFF		
	5 pulse / Pesos 10									OFF	ON		
	10 pulse / Pesos 10									ON	ON		
★	Interface Timing Conversion	50ms on / 50ms off										OFF	OFF
		60ms on / 300ms off										ON	OFF
		30ms on / 50ms off										OFF	ON
		150ms on / 150ms off										ON	ON

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A TYPE Interface Settings: 2(Pulse/RS232)

	INTERFACE	SW1	SW2	SW3	SW4	
★	Credit-Pulse Normal HIGH	ON				
	Credit-Pulse Normal LOW	OFF				
★	Pulse Mode		ON			
	RS232 Interface		OFF			
★	Reserved			ON		
				OFF		
					ON	
					OFF	

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4	
★	Reserved	ON				
		OFF				
	Pulse Mode		ON			
★	RS232 Interface		OFF			
★	Reserved			ON		
				OFF		
					ON	
					OFF	

★ Manufacture setting

V TYPE Interface Settings: 2(Pulse/M.D.B)

	INTERFACE	SW1	SW2	SW3	SW4	
★	Credit-Pulse Normal HIGH	ON				
	Credit-Pulse Normal LOW	OFF				
★	Pulse Mode		ON			
	M.D.B Interface		OFF			
★	Reserved			ON		
				OFF		
					ON	
					OFF	

★ Manufacture setting

	FUNCTION	SW1	SW2	SW3	SW4	
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON				
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF				
	Pulse Mode		ON			
★	M.D.B Interface		OFF			
★	Reserved			ON		
				OFF		
					ON	
					OFF	

★ Manufacture setting