

TAO-A.V-IDR7

TAO-A.V Option Switch Settings: 1(Pulse/ICT/MDB/ICT for VCCS)

Supported bill Rp 1000, 2000, 5000, 10000, 20000, 50000, 100000 7bills.

TAO-V dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Rp 1000 & 2000	ON											
★	Accept Rp 1000 & 2000	OFF											
	Reject Rp 5000 & 10000		ON										
★	Accept Rp 5000 & 10000		OFF										
★	Reject Rp 20000 & 50000			ON									
★	Accept Rp 20000 & 50000			OFF									
★	Reject Rp 100000				ON								
★	Accept Rp 100000				OFF								
★	Reserved				ON								
★	Reserved				OFF								
★	Reserved				ON								
★	Reserved				OFF								
★	Harness Disable							ON					
★	Harness Enable							OFF					
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / Rp 1000									OFF	OFF		
	5 pulses / Rp 1000									ON	OFF		
	10 pulses / Rp 1000									OFF	ON		
	20 pulses / Rp 1000									ON	ON		
★	Interface Timing Conversion	50ms on / 50ms off								OFF	OFF		
		60ms on / 300ms off								ON	OFF		
		30ms on / 50ms off								OFF	ON		
		150ms on / 150ms off								ON	ON		

★ Manufacture setting

◆ Note : (1)Please reset the bill acceptor after any changes on Dip switch.

(2)SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

Appendix

TAO-A.V-IDR7

Interface Settings: 3(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT Mode		OFF	OFF	
	ICT for VCCS		OFF	ON	
	MDB Interface		ON	ON	
★	Reserved			ON	
				OFF	

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB	Pulse
BV1	1000	1000
BV2	2000	2000
BV3	5000	5000
BV4	10000	10000
BV5	20000	20000
BV6	50000	50000
BV7	100000	100000

Interface Settings: 3(ICT/ICT for VCCS)

	INTERFACE	SW1	SW2	SW3	SW4
★	Not Used	ON			
	Not Used	OFF			
	Pulse Mode		ON	OFF	
★	ICT Mode		OFF	OFF	
	ICT for VCCS		OFF	ON	
	MDB Interface		ON	ON	
★	Reserved			ON	
				OFF	

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Not Used	ON			
	Not Used	OFF			
	Pulse Mode		ON	OFF	
	ICT Mode		OFF	OFF	
★	ICT for VCCS		OFF	ON	
	MDB Interface		ON	ON	
★	Reserved			ON	
				OFF	

★ Manufacture setting

TAO-V-IDR7

Interface Settings: 3(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT Mode		OFF	OFF	
	ICT for VCCS		OFF	ON	
★	MDB Interface		ON	ON	
★	Reserved			ON	
				OFF	

★ Manufacture setting