

**TAO-A/V Option Switch Settings: 1**

**Supported bill M\$ 1, 2, 5**

**3bills.**

TAO-A/V dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject M\$ 1	ON											
★	Accept M\$ 1	OFF											
	Reject M\$ 2		ON										
★	Accept M\$ 2		OFF										
	Reject M\$ 5			ON									
★	Accept M\$ 5			OFF									
	Reserved				ON								
★	Reserved				OFF								
	Reserved					ON							
★	Reserved					OFF							
	Reserved						ON						
★	Reserved						OFF						
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
	1 pulse / M\$ 1									OFF	OFF		
★	2 pulses / M\$ 1									ON	OFF		
	4 pulses / M\$ 1									OFF	ON		
	20 pulses / M\$ 1									ON	ON		
★	Interface Timing Conversion	50ms on / 50ms off									OFF	OFF	
		60ms on / 300ms off									ON	OFF	
		30ms on / 50ms off									OFF	ON	
		150ms on / 150ms off									ON	ON	

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

**A TYPE Interface Settings: 2(Pulse/RS232)**

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	RS232 Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
					OFF

★ Manufacture setting

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON		
★	RS232 Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
					OFF

★ Manufacture setting

**V TYPE Interface Settings: 2(Pulse/M.D.B)**

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	M.D.B Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
					OFF

★ Manufacture setting

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	M.D.B Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
					OFF

★ Manufacture setting