

TAO-A.V-PHP6

TAO-A.V Option Switch Settings: 1(Pulse/ICT/MDB/ICT for VCCS)

Supported bill ₱ 20, 50, 100, 200, 500, 1000 6 bills.

TAO-V dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject ₱ 20	ON											
★ Accept ₱ 20	OFF											
★ Reject ₱ 50		ON										
★ Accept ₱ 50		OFF										
★ Reject ₱ 100 & 200			ON									
★ Accept ₱ 100 & 200			OFF									
★ Reject ₱ 500				ON								
★ Accept ₱ 500				OFF								
★ Reject ₱ 1000					ON							
★ Accept ₱ 1000					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / ₱ 10									OFF	OFF		
5 pulses / ₱ 10									ON	OFF		
10 pulses / ₱ 10									OFF	ON		
20 pulses / ₱ 10									ON	ON		
★ Interface Timing Conversion	50ms off / 50ms off								OFF	OFF		
	60ms on / 300ms off								ON	OFF		
	30ms off / 50ms on								OFF	ON		
	150ms on / 150ms on								ON	ON		

★ Manufacture setting

◆ Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

TAO-A.V-PHP6

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT Mode		OFF	OFF	
ICT for VCCS		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse	MDB
BV1	₱ 20	₱ 20	₱ 20
BV2	₱ 50	₱ 50	₱ 50
BV3	₱ 100	₱ 100	₱ 100
BV4	₱ 500	₱ 200	₱ 200
BV5	₱ 1000	₱ 500	₱ 500
BV6	₱ 200	₱ 1000	₱ 1000

Interface Settings: 2(ICT/ICT for VCCS)

INTERFACE	SW1	SW2	SW3	SW4
★ Not Used	ON			
Not Used	OFF			
Pulse Mode		ON	OFF	
★ ICT Mode		OFF	OFF	
ICT for VCCS		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

★ Manufacture setting

TAO-V-PHP6

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT Mode		OFF	OFF	
ICT for VCCS		OFF	ON	
★ MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting