

TAO-A/V Option Switch Settings: 1

Supported bill S\$ 2, 5

2bills.

TAO-A/V dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject S\$ 2	ON											
★	Accept S\$ 2	OFF											
	Reject S\$ 5		ON										
★	Accept S\$ 5		OFF										
	Reserved			ON									
★	Reserved			OFF									
	Reserved				ON								
★	Reserved				OFF								
	Reserved					ON							
★	Reserved					OFF							
	Reserved						ON						
★	Reserved						OFF						
	Reserved							ON					
★	Reserved							OFF					
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / S\$ 1									OFF	OFF		
	2 pulses / S\$ 1									ON	OFF		
	4 pulses / S\$ 1									OFF	ON		
	20 pulses / S\$ 1									ON	ON		
★	Interface Timing Conversion	50ms on / 50ms off										OFF	OFF
		60ms on / 300ms off										ON	OFF
		30ms on / 50ms off										OFF	ON
		150ms on / 150ms off										ON	ON

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A TYPE Interface Settings: 2(Pulse/RS232)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
RS232 Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON		
★ RS232 Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

V TYPE Interface Settings: 2(Pulse/M.D.B)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
M.D.B Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0		ON		
★ Pulse Mode		OFF		
★ M.D.B Interface			ON	
★ Reserved			OFF	
				ON
				OFF
				ON

★ Manufacture setting