

A6/V6 Option Switch Settings

Supported bill \$ 2(97), 5(98), 10(98), 20(00), 50(99), 100(99)
 6 bills.

A6/V6 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
Reject \$ 2	ON											
Accept \$ 2	OFF											
Reject \$ 5		ON										
Accept \$ 5		OFF										
Reject \$ 10			ON									
Accept \$ 10			OFF									
Reject \$ 20				ON								
Accept \$ 20				OFF								
Reject \$ 50 & 100					ON							
Accept \$ 50 & 100					OFF							
Reserved						ON						
Reserved						OFF						
Harness Disable							ON					
Harness Enable							OFF					
Inhibit Active High								ON				
Inhibit Active Low								OFF				
1 pulse / \$ 1									OFF	OFF		
2 pulse / \$ 1									ON	OFF		
4 pulse / \$ 1									OFF	ON		
20 pulse / \$ 1									ON	ON		
Pulse Speed	50ms on / 50ms off								OFF	OFF		
	60ms on / 300ms off								ON	OFF		
	30ms on / 50ms off								OFF	ON		
	150ms on / 150ms off								ON	ON		

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A6 Interface Settings: 2

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
	Pulse Mode		ON		
★	RS232 Interface		OFF		
	HOLD			ON	
				OFF	
					ON
					OFF

★ Manufacture setting

V6 Interface Settings: 3

	INTERFACE	SW1	SW2	SW3	SW4
	HOLD	ON			
		OFF			
	Pulse Mode		ON		
★	MDB Interface		OFF		
	HOLD			ON	
				OFF	
					ON
					OFF

★ Manufacture setting