

A6/V6-AUD5

A6/V6 Option Switch Settings: 1

Supported bill \$A 5, 10, 20, 50, 100 5bills.

A6/V6 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject \$A 5	ON											
★ Accept \$A 5	OFF											
★ Reject \$A 10		ON										
★ Accept \$A 10		OFF										
★ Reject \$A 20			ON									
★ Accept \$A 20			OFF									
★ Reject \$A 50				ON								
★ Accept \$A 50				OFF								
★ Reject \$A 100					ON							
★ Accept \$A 100					OFF							
★ High Acceptance (Note.3)						ON						
★ High Security						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / \$A 5									OFF	OFF		
★ 5 pulse / \$A 5									ON	OFF		
★ 10 pulse / \$A 5									OFF	ON		
★ 20 pulse / \$A 5									ON	ON		
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

A6/V6-AUD5

A6 Interface Settings: 2(Pulse/ICT002)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
ICT002 Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Pulse Mode		ON		
★ ICT002 Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

V6 Interface Settings: 2(M.D.B)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
★ Reserved		ON		
★ M.D.B Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT002
BV1	\$A 5	\$A 5
BV2	\$A 10	\$A 10
BV3	\$A 20	\$A 20
BV4	\$A 50	\$A 50
BV5	\$A 100	\$A 100

Currency Assign Data

Interface Bill value	MDB
BV1	\$A 5
BV2	\$A 10
BV3	\$A 20
BV4	\$A 50
BV5	\$A 100