

## V7-GBP2

### V7 Option Switch Settings : 1(Pulse/MDB/ICT004U)

#### Supported bill

England banknotes : Bank of England £ 5, £ 10

Scotland banknotes: Bank of Scotland £ 5, £ 10

Royal Bank of Scotland £ 5, £ 10

V7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject GBP 5	ON											
★ Accept GBP 5	OFF											
★ Reject GBP 10		ON										
★ Accept GBP 10		OFF										
★ Reserved			ON									
★ Reserved			OFF									
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / GBP 5									OFF	OFF		
★ 5 pulses / GBP 5									ON	OFF		
★ 10 pulses / GBP 5									OFF	ON		
★ 20 pulses / GBP 5									ON	ON		
★ Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

## V7-GBP2 (PULSE/MDB/ICT004U)

### V7 Interface Settings: 3 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
★ Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
★ MDB Mode		OFF	OFF	
★ ICT004U Mode		OFF	ON	
★ Reserved		ON	ON	
★ Reserved				ON
★ Reserved				OFF

★ Manufacture setting

### V7 Interface Settings: 3 (MDB)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
★ Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★ Pulse Mode		ON	OFF	
★ MDB Mode		OFF	OFF	
★ ICT004U Mode		OFF	ON	
★ Reserved		ON	ON	
★ Reserved				ON
★ Reserved				OFF

★ Manufacture setting

### V7 Interface Settings: 3 (ICT004U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
★ Reserved	OFF			
★ Pulse Mode		ON	OFF	
★ MDB Mode		OFF	OFF	
★ ICT004U Mode		OFF	ON	
★ Reserved		ON	ON	
★ Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Note: (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "SW1" setting.)

### Currency Assign Data

Interface Bill value	Pulse	MDB	ICT004U
BV1	GBP 5	GBP 5	GBP 5
BV2	GBP 10	GBP 10	GBP 10