

V7-KRW3

V7 Option Switch Settings: 1 (Pulse/ICT004/MDB)

Supported bill KRW 1000, 5000, 10000 3bills.

V7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject KRW 1000	ON											
★ Accept KRW 1000	OFF											
★ Reject KRW 5000		ON										
★ Accept KRW 5000		OFF										
★ Reject KRW 10000			ON									
★ Accept KRW 10000			OFF									
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 Pulse / KRW1000									OFF	OFF		
5 Pulses / KRW1000									ON	OFF		
10 Pulses / KRW1000									OFF	ON		
20 Pulses / KRW1000									ON	ON		
★ Pulse Speed	50ms LO / 50ms HI										OFF	OFF
	60ms LO / 300ms HI										ON	OFF
	30ms LO / 50ms HI										OFF	ON
	150ms LO / 150ms HI										ON	ON

◆ Factory configuration has all switches in the OFF position.

★ Manufacture setting

V7-KRW3(Pulse/ICT004/MDB)

V7 Interface Settings: 3 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
MDB Interface		OFF	OFF	
ICT004 Interface		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

V7 Interface Settings: 3 (ICT004)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Pulse Mode		ON	OFF	
MDB Interface		OFF	OFF	
★ ICT004 Interface		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

V7 Interface Settings: 3 (MDB)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 10 Decimal Point Position (DPP) = 1	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ MDB Interface		OFF	OFF	
ICT004 Interface		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Note: 1.Default setting.

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "Sw1" setting.)

Currency Assign Data

Interface Bill value	ICT004	Pulse	MDB
BV1	KRW 1000	KRW 1000	KRW 1000
BV2	KRW 5000	KRW 5000	KRW 5000
BV3	KRW10000	KRW10000	KRW10000