

## V7-MYR6

### V7 Option Switch Settings: 1 (Pulse/ICT004/MDB)

Supported bill MYR 1, 5, 10, 20, 50, 100 6bills.

V7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject M\$ 1	ON											
★ Accept M\$ 1	OFF											
★ Reject M\$ 5		ON										
★ Accept M\$ 5		OFF										
★ Reject M\$ 10 & 20			ON									
★ Accept M\$ 10 & 20			OFF									
★ Reject M\$ 50				ON								
★ Accept M\$ 50				OFF								
★ Reject M\$ 100					ON							
★ Accept M\$ 100					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 Pulse / M\$ 1									OFF	OFF		
★ 2 Pulses / M\$ 1									ON	OFF		
★ 5 Pulses / M\$ 1									OFF	ON		
★ 10 Pulses / M\$ 1									ON	ON		
★ Pulse Speed	50ms LO / 50ms HI										OFF	OFF
	60ms LO / 300ms HI										ON	OFF
	30ms LO / 50ms HI										OFF	ON
	150ms LO / 150ms HI										ON	ON

◆ Factory configuration has all switches in the OFF position.

★ Manufacture setting

## V7-MYR6(Pulse/ICT004/MDB)

### V7 Interface Settings: 3 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
MDB Interface		OFF	OFF	
ICT004 Interface		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

### V7 Interface Settings: 3 (ICT004)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
MDB Interface		OFF	OFF	
★ ICT004 Interface		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

### V7 Interface Settings: 3 (MDB)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ MDB Interface		OFF	OFF	
ICT004 Interface		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Note: 1.Default setting.

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "Sw1" setting.)

### Currency Assign Data

Interface Bill value	ICT004	Pulse	MDB
BV1	MYR 1	MYR 1	MYR 1
BV2			
BV3	MYR 5	MYR 5	MYR 5
BV4	MYR 10	MYR 10	MYR 10
BV5	MYR 50	MYR 50	MYR 50
BV6	MYR 100	MYR 100	MYR 100
BV7	MYR 20	MYR 20	MYR 20