

V7-NZD3

V7 Option Switch Settings: 1 (Pulse/ICT004/MDB)

Supported bill NZD 5, 10, 20 3bills.

V7 dip-switch settings and functions:

| FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 |
|-----------------------|---------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| ★ Reject NZ\$ 5 | ON | | | | | | | | | | | |
| ★ Accept NZ\$ 5 | OFF | | | | | | | | | | | |
| ★ Reject NZ\$ 10 | | ON | | | | | | | | | | |
| ★ Accept NZ\$ 10 | | OFF | | | | | | | | | | |
| ★ Reject NZ\$ 20 | | | ON | | | | | | | | | |
| ★ Accept NZ\$ 20 | | | OFF | | | | | | | | | |
| ★ Reserved | | | | ON | | | | | | | | |
| ★ Reserved | | | | OFF | | | | | | | | |
| ★ Reserved | | | | | ON | | | | | | | |
| ★ Reserved | | | | | OFF | | | | | | | |
| ★ Reserved | | | | | | ON | | | | | | |
| ★ Reserved | | | | | | OFF | | | | | | |
| ★ Harness Disable | | | | | | | ON | | | | | |
| ★ Harness Enable | | | | | | | OFF | | | | | |
| ★ Inhibit Active High | | | | | | | | ON | | | | |
| ★ Inhibit Active Low | | | | | | | | OFF | | | | |
| ★ 1 Pulse / NZ\$ 5 | | | | | | | | | OFF | OFF | | |
| ★ 5 Pulses / NZ\$ 5 | | | | | | | | | ON | OFF | | |
| ★ 10 Pulses / NZ\$ 5 | | | | | | | | | OFF | ON | | |
| ★ 25 Pulses / NZ\$ 5 | | | | | | | | | ON | ON | | |
| ★ Pulse Speed | 50ms LO / 50ms HI | | | | | | | | | | OFF | OFF |
| | 60ms LO / 300ms HI | | | | | | | | | | ON | OFF |
| | 30ms LO / 50ms HI | | | | | | | | | | OFF | ON |
| | 150ms LO / 150ms HI | | | | | | | | | | ON | ON |

◆ Factory configuration has all switches in the OFF position.

★ Manufacture setting

V7-NZD3(Pulse/ICT004/MDB)

V7 Interface Settings: 3 (Pulse)

| INTERFACE | SW1 | SW2 | SW3 | SW4 |
|----------------------------|-----|-----|-----|-----|
| ★ Credit-Pulse Normal High | ON | | | |
| Credit-Pulse Normal Low | OFF | | | |
| ★ Pulse Mode | | ON | OFF | |
| ★ MDB Interface | | OFF | OFF | |
| ICT004 Interface | | OFF | ON | |
| Reserved | | ON | ON | |
| ★ Reserved | | | | ON |
| | | | | OFF |

★ Manufacture setting

V7 Interface Settings: 3 (ICT004)

| INTERFACE | SW1 | SW2 | SW3 | SW4 |
|--------------------|-----|-----|-----|-----|
| ★ Reserved | ON | | | |
| ★ Reserved | OFF | | | |
| ★ Pulse Mode | | ON | OFF | |
| MDB Interface | | OFF | OFF | |
| ★ ICT004 Interface | | OFF | ON | |
| Reserved | | ON | ON | |
| ★ Reserved | | | | ON |
| | | | | OFF |

★ Manufacture setting

V7 Interface Settings: 3 (MDB)

| INTERFACE | SW1 | SW2 | SW3 | SW4 |
|---|-----|-----|-----|-----|
| ★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2 | ON | | | |
| Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0 | OFF | | | |
| Pulse Mode | | ON | OFF | |
| ★ MDB Interface | | OFF | OFF | |
| ICT004 Interface | | OFF | ON | |
| Reserved | | ON | ON | |
| ★ Reserved | | | | ON |
| | | | | OFF |

★ Manufacture setting

Note: 1.Default setting.

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "Sw1" setting.)

Currency Assign Data

| Interface Bill value | ICT004 | Pulse | MDB |
|-------------------------|---------|---------|---------|
| BV1 | NZ\$ 5 | NZ\$ 5 | NZ\$ 5 |
| BV2 | NZ\$ 10 | NZ\$ 10 | NZ\$ 10 |
| BV3 | NZ\$ 20 | NZ\$ 20 | NZ\$ 20 |