

## V7-SGD3

### V7 Option Switch Settings : 1(Pulse/MDB/ICT004U)

Supported bill SGD 2, 5, 10 3bills.

V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject SGD 2	ON											
	Accept SGD 2	OFF											
	Reject SGD 5		ON										
★	Accept SGD 5		OFF										
	Reject SGD 10			ON									
★	Accept SGD 10			OFF									
	Reserved				ON								
★	Reserved				OFF								
	Reserved					ON							
★	Reserved					OFF							
	Reserved						ON						
★	Reserved						OFF						
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / SGD 1									OFF	OFF		
	2 pulses / SGD 1									ON	OFF		
	4 pulses / SGD 1									OFF	ON		
	20 pulses / SGD 1									ON	ON		
★	Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

## V7-SGD3 (Pulse/MDB/ICT004U)

### V7 Interface Settings: 3 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	MDB Mode		OFF	OFF	
	ICT004U Mode		OFF	ON	
	Reserved		ON	ON	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

### V7 Interface Settings: 3 (MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
★	MDB Mode		OFF	OFF	
	ICT004U Mode		OFF	ON	
	Reserved		ON	ON	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

### V7 Interface Settings: 3 (ICT004U)

	INTERFACE	SW1	SW2	SW3	SW4
	Reserved	ON			
★	Reserved	OFF			
	Pulse Mode		ON	OFF	
	MDB Mode		OFF	OFF	
★	ICT004U Mode		OFF	ON	
	Reserved		ON	ON	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Note: (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "SW1" setting.)

### Currency Assign Data

Interface Bill value	Pulse	MDB	ICT004U
BV1	SGD 2	SGD 2	SGD 2
BV2	SGD 5	SGD 5	SGD 5
BV3	SGD 10	SGD 10	SGD 10