

V7-TWD4

V7 Option Switch Settings: 1 (Pulse/ICT004/MDB)

Supported bill TWD 100, 200, 500, 1000 4bills.

V7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject TWD 100	ON											
★ Accept TWD 100	OFF											
★ Reject TWD 200		ON										
★ Accept TWD 200		OFF										
★ Reject TWD 500			ON									
★ Accept TWD 500			OFF									
★ Reject TWD 1000				ON								
★ Accept TWD 1000				OFF								
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 Pulse / TWD 100									OFF	OFF		
2 Pulses / TWD 100									ON	OFF		
4 Pulses / TWD 100									OFF	ON		
20 Pulses / TWD 100									ON	ON		
★ Pulse Speed	50ms LO / 50ms HI										OFF	OFF
	60ms LO / 300ms HI										ON	OFF
	30ms LO / 50ms HI										OFF	ON
	150ms LO / 150ms HI										ON	ON

◆ Factory configuration has all switches in the OFF position.

★ Manufacture setting

V7-TWD4(Pulse/ICT004/MDB)

V7 Interface Settings: 3 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
MDB Interface		OFF	OFF	
ICT004 Interface		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

V7 Interface Settings: 3 (ICT004)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Pulse Mode		ON	OFF	
MDB Interface		OFF	OFF	
★ ICT004 Interface		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

V7 Interface Settings: 3 (MDB)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ MDB Interface		OFF	OFF	
ICT004 Interface		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Note: 1.Default setting.

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "Sw1" setting.)

Currency Assign Data

Interface Bill value	ICT004	Pulse	MDB
BV1	TWD 100	TWD 100	TWD 100
BV2	TWD 200	TWD 200	TWD 200
BV3	TWD 500	TWD 500	TWD 500
BV4	TWD 1000	TWD 1000	TWD 1000