

V7E/LX7-MYR6

V7E/LX7 Option Switch Settings: 1(Pulse/ICT/MDB/ICT for VCCS)

Supported bill M\$ 1, 5, 10, 20, 50, 100 6bills.

V7E/LX7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject M\$ 1	ON											
★ Accept M\$ 1	OFF											
★ Reject M\$ 5		ON										
★ Accept M\$ 5		OFF										
★ Reject M\$ 10 - 20			ON									
★ Accept M\$ 10 - 20			OFF									
★ Reject M\$ 50				ON								
★ Accept M\$ 50				OFF								
★ Reject M\$ 100					ON							
★ Accept M\$ 100					OFF							
★ Reserved					ON							
★ Reserved					OFF							
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / M\$ 1									OFF	OFF		
★ 5 pulses / M\$ 1									ON	OFF		
★ 10 pulses / M\$ 1									OFF	ON		
★ 25 pulses / M\$ 1									ON	ON		
★ Interface Timing Conversion	50ms on / 50ms off										OFF	OFF
	60ms on / 300ms off										ON	OFF
	30ms on / 50ms off										OFF	ON
	150ms on / 150ms off										ON	ON

★ Manufacture setting

◆ Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) BV1=M\$1, BV3=M\$5, BV4=M\$10, BV5=M\$50, BV6=M\$100, BV7=M\$20.

V7E/LX7-MYR6

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT Mode		OFF	OFF	
ICT for VCCS		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse	MDB
BV1	M\$ 1	M\$ 1	M\$ 1
BV3	M\$ 5	M\$ 5	M\$ 5
BV4	M\$ 10	M\$ 10	M\$ 10
BV5	M\$ 50	M\$ 50	M\$ 50
BV6	M\$ 100	M\$ 100	M\$ 100
BV7	M\$ 20	M\$ 20	M\$ 20

Interface Settings: 2(ICT/ICT for VCCS)

INTERFACE	SW1	SW2	SW3	SW4
★ Not Used	ON			
Not Used	OFF			
Pulse Mode		ON	OFF	
★ ICT Mode		OFF	OFF	
ICT for VCCS		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Not Used	ON			
Not Used	OFF			
Pulse Mode		ON	OFF	
★ ICT Mode		OFF	OFF	
ICT for VCCS		OFF	ON	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT Mode		OFF	OFF	
ICT for VCCS		OFF	ON	
★ MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting