

V7E/LX7-SRD5

V7E/LX7 Option Switch Settings: 1(Pulse/ICT002)

Supported bill SRD 5, 10, 20, 50, 100 5bills.

V7E/LX7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	
★	Reject SRD 5	ON												
	Accept SRD 5	OFF												
★	Reject SRD 10		ON											
★	Accept SRD 10		OFF											
★	Reject SRD 20			ON										
★	Accept SRD 20			OFF										
★	Reject SRD 50				ON									
★	Accept SRD 50				OFF									
★	Reject SRD 100					ON								
★	Accept SRD 100					OFF								
	Reserved					ON								
★	Reserved					OFF								
	Pulse Mode	Other Mode												
★	Harness Disable	BA stops working when fishing						ON						
★	Harness Enable	Normal						OFF						
★	Inhibit Active High							ON						
★	Inhibit Active Low							OFF						
★	1 pulse / SRD 5							OFF	OFF					
	2 pulses / SRD 5							ON	OFF					
	4 pulses / SRD 5							OFF	ON					
	5 pulses / SRD 5							ON	ON					
★	Pulse Speed	50ms LO / 50ms HI							OFF	OFF				
		60ms LO / 300ms HI							ON	OFF				
		30ms LO / 50ms HI							OFF	ON				
		150ms LO / 150ms HI							ON	ON				

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

Appendix

V7E/LX7-SRD5(Pulse/ICT002)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT002 Interface		OFF		
★	Reserved			ON	
				OFF	
★	Reserved				ON
					OFF

DIP SWITCHES SETTING : 2(ICT002)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON		
★	ICT002 Interface		OFF		
★	Reserved			ON	
				OFF	
★	Reserved				ON
					OFF

Currency Assign Data

Interface Bill value	Pulse	ICT002
BV1		
BV2	SRD 5	SRD 5
BV3	SRD 10	SRD 10
BV4	SRD 20	SRD 20
BV5	SRD 100	SRD 100
BV6	SRD 50	SRD 50