

NK77F-KHR9

NK77F DIP SWITCHES SETTING : (Pulse/ICT104U)

Supported bill KHR 100, 500, 1000, 2000, 5000, 10000, 20000,
50000, 100000 9bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / KHR 100	OFF	OFF									
	2 Pulses / KHR 100	OFF	ON									
	5 Pulses / KHR 100	ON	OFF									
	10 Pulses / KHR 100	ON	ON									
	Enable Fish Stop			ON								
★	Disable Fish Stop			OFF								
★	Inhibit level Active Low				ON							
	Inhibit level Active High				OFF							
★	Accept KHR 100 & 500 & 1000 & 2000 & 5000 & 10000					ON						
	Reject KHR 100 & 500 & 1000 & 2000 & 5000 & 10000					OFF						
★	Accept KHR 20000 & 50000 & 100000						ON					
	Reject KHR 20000 & 50000 & 100000						OFF					
	Enable Output Sensor Detect								ON			
★	Disable Output Sensor Detect								OFF			
★	Pulse Normal High									ON		
	Pulse Normal Low									OFF		
★	Pulse Mode										ON	
	ICT104U Mode										OFF	
★	Power On Motor Plus											ON
	Power On Motor Minus											OFF

★ Manufacture setting
Note: (1) Please reset the bill acceptor after set the dip switch.
(2) Pulse speed is LO=50ms/HI=100ms.

NK77F-KHR9(Pulse/ICT104U)

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	KHR 100	KHR 100
BV2	KHR 500	KHR 500
BV3	KHR 1000	KHR 1000
BV4	KHR 2000	KHR 2000
BV5	KHR 5000	KHR 5000
BV6	KHR 10000	KHR 10000
BV7	KHR 20000	KHR 20000
BV8	KHR 50000	KHR 50000
BV9	KHR 100000	KHR 100000