

V7P-SYP6

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill SYP 10, 25, 50, 100, 200, 500 6bills.

V7P dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject SYP 10 & 25	ON											
	Accept SYP 10 & 25	OFF											
	Reject SYP 50		ON										
★	Accept SYP 50		OFF										
	Reject SYP 100			ON									
★	Accept SYP 100			OFF									
	Reject SYP 200				ON								
★	Accept SYP 200				OFF								
	Reject SYP 500					ON							
★	Accept SYP 500					OFF							
	Reserved						ON						
★	Reserved						OFF						
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / SYP 5									OFF	OFF		
	2 pulses / SYP 5									ON	OFF		
	4 pulses / SYP 5									OFF	ON		
	20 pulses / SYP 5									ON	ON		
★	Interface Timing Conversion	50ms LO / 50ms HI										OFF	OFF
		60ms LO / 300ms HI										ON	OFF
		30ms LO / 50ms HI										OFF	ON
		150ms LO / 150ms HI										ON	ON

★ Manufacture setting

Note : (1) Dip Switch 1 is for Pulse

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

V7P-SYP6(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	MDB	Pulse
BV1	SYP 10	SYP 10	SYP 10	SYP 10
BV2	SYP 25	SYP 25	SYP 25	SYP 25
BV3	SYP 50	SYP 50	SYP 50	SYP 50
BV4	SYP 100	SYP 100	SYP 100	SYP 100
BV5	SYP 200	SYP 200	SYP 200	SYP 200
BV6	SYP 500	SYP 500	SYP 500	SYP 500

Interface Settings: 2(ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
★	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting