

L70/L70F-CRC5

L70/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill CRC 1000, 2000, 5000, 10000, 20000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / CRC 1000	OFF	OFF	OFF							
	2 Pulses / CRC 1000	OFF	OFF	ON							
	3 Pulses / CRC 1000	OFF	ON	OFF							
	4 Pulses / CRC 1000	OFF	ON	ON							
	5 Pulses / CRC 1000	ON	OFF	OFF							
	10 Pulses / CRC 1000	ON	OFF	ON							
	20 Pulses / CRC 1000	ON	ON	OFF							
	100 Pulses / CRC 1000	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept CRC 1000					ON					
	Reject CRC 1000					OFF					
★	Accept CRC 2000						ON				
	Reject CRC 2000						OFF				
★	Accept CRC 5000							ON			
	Reject CRC 5000							OFF			
★	Accept CRC 10000								ON		
	Reject CRC 10000								OFF		
★	Accept CRC 20000									ON	
	Reject CRC 20000									OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.
(2) Dip switches 1 to 5 are only used for pulse protocol.

L70/L70F-CRC5(Pulse/ICT104U/MDB/ICT104V)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	CRC 1000	CRC 1000	CRC 1000	CRC 1000
BV2	CRC 2000	CRC 2000	CRC 2000	CRC 2000
BV3	CRC 5000	CRC 5000	CRC 5000	CRC 5000
BV4	CRC 10000	CRC 10000	CRC 10000	CRC 10000
BV5	CRC 20000	CRC 20000	CRC 20000	CRC 20000

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
★	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
★	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting