

L70+L70F-NAD10(NAD7+ZAR3)

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill NAD 10, 20, 30, 50, 60, 100, 200 7 bills.
ZAR 50, 100, 200 3 bills.

★	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / NAD & ZAR 10	OFF	OFF	OFF							
	2 Pulses / NAD & ZAR 10	OFF	OFF	ON							
	3 Pulses / NAD & ZAR 10	OFF	ON	OFF							
	4 Pulses / NAD & ZAR 10	OFF	ON	ON							
	5 Pulses / NAD & ZAR 10	ON	OFF	OFF							
	10 Pulses / NAD & ZAR 10	ON	OFF	ON							
	20 Pulses / NAD & ZAR 10	ON	ON	OFF							
	100 Pulses / NAD & ZAR 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept NAD 10 & NAD 20 & NAD 30 & NAD 60				ON						
	Reject NAD 10 & NAD 20 & NAD 30 & NAD 60				OFF						
★	Accept NAD 50 & ZAR 50				ON						
	Reject NAD 50 & ZAR 50				OFF						
★	Accept NAD 100 & ZAR 100				ON						
	Reject NAD 100 & ZAR 100				OFF						
★	Accept NAD 200 & ZAR 200				ON						
	Reject NAD 200 & ZAR 200				OFF						
	Accept NAD ONLY				ON						
★	Accept NAD and ZAR				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70+L70F-NAD10(NAD7+ZAR3)(Pulse/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT104U Interface Mode		OFF		
★	Reserved			ON	
				OFF	
★	Reserved			ON	
				OFF	

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON		
	ICT104U Interface Mode		OFF		
★	Reserved			ON	
				OFF	
★	Reserved			ON	
				OFF	

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	NAD 10	NAD 10
BV2	NAD 20	NAD 20
BV3	NAD 50	NAD 50
BV4	NAD 100	NAD 100
BV5	NAD 200	NAD 200
BV6	NAD 30	NAD 30
BV7	NAD 60	NAD 60
BV8	ZAR 50	ZAR 50
BV9	ZAR 100	ZAR 100
BV10	ZAR 200	ZAR 200