

L70+/L70F-BRA6

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill R\$ 2, 5, 10, 20, 50, 100

6bills.

★	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / R\$ 1	OFF	OFF								
	2 Pulse / R\$ 1	OFF	ON								
	4 Pulse / R\$ 1	ON	OFF								
	10 Pulse / R\$ 1	ON	ON								
★	Output Pulse Lo= 50ms Hi=100ms			OFF	OFF						
	Output Pulse Lo=150ms Hi=100ms			OFF	ON						
	Output Pulse Lo= 20ms Hi=100ms			ON	OFF						
	Output Pulse Lo= 30ms Hi=150ms			ON	ON						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept R\$ 2					ON					
	Reject R\$ 2					OFF					
★	Accept R\$ 5						ON				
	Reject R\$ 5						OFF				
★	Accept R\$ 10							ON			
	Reject R\$ 10							OFF			
★	Accept R\$ 20								ON		
	Reject R\$ 20								OFF		
★	Accept R\$ 50 & 100									ON	
	Reject R\$ 50 & 100									OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	R\$ 1	R\$ 1
BV2	R\$ 2	R\$ 2
BV3	R\$ 5	R\$ 5
BV4	R\$ 10	R\$ 10
BV5	R\$ 20	R\$ 20
BV6	R\$ 50	R\$ 50
BV7	R\$ 100	R\$ 100

L70+/L70F-BRA6(Pulse/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT104U Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Disable Inverse Mode				ON
★	Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	ICT104U Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Disable Inverse Mode				ON
★	Enable Inverse Mode				OFF

★ Manufacture setting