

L70/L70F-TJS6

L70/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill TJS 1, 3, 5, 10, 20, 50 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / TJS 1	OFF	OFF	OFF							
	2 Pulses / TJS 1	OFF	OFF	ON							
	3 Pulses / TJS 1	OFF	ON	OFF							
	4 Pulses / TJS 1	OFF	ON	ON							
	5 Pulses / TJS 1	ON	OFF	OFF							
	10 Pulses / TJS 1	ON	OFF	ON							
	20 Pulses / TJS 1	ON	ON	OFF							
	100 Pulses / TJS 1	ON	ON	ON							
★	Fast output Pulse Lo= 50ms Hi=100ms				ON						
	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
★	Inhibit level Active Low					ON					
	Inhibit level Active High					OFF					
★	Accept TJS 1						ON				
	Reject TJS 1						OFF				
★	Accept TJS 3							ON			
	Reject TJS 3							OFF			
★	Accept TJS 5 & 10								ON		
	Reject TJS 5 & 10								OFF		
★	Accept TJS 20									ON	
	Reject TJS 20									OFF	
★	Accept TJS 50										ON
	Reject TJS 50										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.
(2) Dip switches 1 to 5 are only used for pulse protocol.

L70/L70F-TJS6(Pulse/ICT104U/MDB/ICT104V)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse	MDB	ICT104V
BV1	TJS 1	TJS 1	TJS 1	TJS 1
BV2	TJS 3	TJS 3	TJS 3	TJS 3
BV3	TJS 5	TJS 5	TJS 5	TJS 5
BV4	TJS 10	TJS 10	TJS 10	TJS 10
BV5	TJS 20	TJS 20	TJS 20	TJS 20
BV6	TJS 50	TJS 50	TJS 50	TJS 50

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
★	MDB Mode		ON	ON	
	ICT104V Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting