

TAO-V+SYP6

TAO-V Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill SYP 10, 25, 50, 100, 200, 500 6bills.

TAO-V dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject SYP 10 & 25	ON											
	Accept SYP 10 & 25	OFF											
★	Reject SYP 50		ON										
★	Accept SYP 50		OFF										
★	Reject SYP 100			ON									
★	Accept SYP 100			OFF									
★	Reject SYP 200				ON								
★	Accept SYP 200				OFF								
★	Reject SYP 500					ON							
★	Accept SYP 500					OFF							
	Reserved					ON							
★	Reserved					OFF							
	Pulse Mode												
	Other Mode												
	Harness Disable	BA stops working when fishing							ON				
★	Harness Enable	Normal							OFF				
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / SYP 5								OFF	OFF			
	2 pulses / SYP 5								ON	OFF			
	5 pulses / SYP 5								OFF	ON			
	10 pulses / SYP 5								ON	ON			
★	Interface Timing Conversion	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "SW1" setting.)

BV1=SYP 10, BV2=SYP 25, BV3=SYP 50, BV4=SYP 100, BV5=SYP 200, BV6=SYP 500

Appendix

TAO-V+SYP6(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104V Mode		OFF	ON	
	ICT104U Mode		OFF	OFF	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
	Reserved	ON			
★	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104V Mode		OFF	ON	
	ICT104U Mode		OFF	OFF	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100	ON			
	Decimal Point Position (DPP) = 2				
	Scaling Factor (SF) = 1	OFF			
	Decimal Point Position (DPP) = 0				
	Pulse Mode		ON	OFF	
	ICT104V Mode		OFF	ON	
	ICT104U Mode		OFF	OFF	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
BV1	SYP 10	SYP 10	SYP 10	SYP 10
BV2	SYP 25	SYP 25	SYP 25	SYP 25
BV3	SYP 50	SYP 50	SYP 50	SYP 50
BV4	SYP 100	SYP 100	SYP 100	SYP 100
BV5	SYP 200	SYP 200	SYP 200	SYP 200
BV6	SYP 500	SYP 500	SYP 500	SYP 500

Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
	Reserved	ON			
★	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104V Mode		OFF	ON	
	ICT104U Mode		OFF	OFF	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting