

## V7-AZN5

### V7 Option Switch Settings: 1 (Pulse/ICT004U/MDB)

Supported bill AZN 1, 5, 10, 20, 50 5bills.

V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8
★	Reject AZN 1	ON							
	Accept AZN 1	OFF							
	Reject AZN 5		ON						
★	Accept AZN 5		OFF						
	Reject AZN 10			ON					
★	Accept AZN 10			OFF					
	Reject AZN 20				ON				
★	Accept AZN 20				OFF				
	Reject AZN 50					ON			
★	Accept AZN 50					OFF			
	Reserved						ON		
★	Reserved						OFF		
	Harness Disable							ON	
★	Harness Enable							OFF	
	Inhibit Active High								ON
★	Inhibit Active Low								OFF

◆ Factory configuration has all switches in the OFF position.

### V7 Interface Settings: 2 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	1 pulse / AZN 1	OFF	OFF		
	2 pulse / AZN 1	ON	OFF		
	5 pulse / AZN 1	OFF	ON		
	20 pulse / AZN 1	ON	ON		
★	50ms LO / 50ms HI			OFF	OFF
	60ms LO / 300ms HI			ON	OFF
	30ms LO / 50ms HI			OFF	ON
	150ms LO / 150ms HI			ON	ON

★ Manufacture setting

## V7-AZN5(Pulse/ICT004U/MDB)

### V7 Interface Settings: 3 (ICT004U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	MDB Interface		OFF	OFF	
★	ICT004U Interface		OFF	ON	
	Reserved		ON	ON	
★	Reserved				ON
					OFF

### V7 Interface Settings: 3 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	MDB Interface		OFF	OFF	
	ICT004U Interface		OFF	ON	
	Reserved		ON	ON	
★	Reserved				ON
					OFF

### V7 Interface Settings: 3 (MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
★	MDB Interface		OFF	OFF	
	ICT004U Interface		OFF	ON	
	Reserved		ON	ON	
★	Reserved				ON
					OFF

### Currency Assign Data

Interface Bill value	Pulse	MDB	ICT004U
BV1	AZN 1	AZN 1	AZN 1
BV2	AZN 5	AZN 5	AZN 5
BV3	AZN 10	AZN 10	AZN 10
BV4	AZN 20	AZN 20	AZN 20
BV5	AZN 50	AZN 50	AZN 50

Note: 1. Reset the bill acceptor after setting the dip switch.

2.SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.