

## BS7-AMD2

### BS7 Option Switch Settings: 1 (Pulse/MDB/ICT004)

Supported bill DRAMS 1000, 2000 2bills.

BS7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8
★	Reject DRAMS 1000	ON							
★	Accept DRAMS 1000	OFF							
★	Reject DRAMS 2000		ON						
★	Accept DRAMS 2000		OFF						
	Reserved			ON					
★	Reserved			OFF					
★	Reserved				ON				
★	Reserved				OFF				
★	Reserved					ON			
★	Reserved					OFF			
★	Reserved						ON		
★	Reserved						OFF		
★	Harness Disable							ON	
★	Harness Enable							OFF	
★	Inhiblit Active High								ON
★	Inhibit Active Low								OFF

◆ Factory configuration has all switches in the OFF position.

### BS7 Interface Settings: 2 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	1 pulse / DRAMS 1000	OFF	OFF		
	2 pulse / DRAMS 1000	ON	OFF		
	4 pulse / DRAMS 1000	OFF	ON		
	20 pulse / DRAMS 1000	ON	ON		
★	50ms LO / 50ms HI			OFF	OFF
	60ms LO / 300ms HI			ON	OFF
	30ms LO / 50ms HI			OFF	ON
	150ms LO / 150ms HI			ON	ON

★ Manufacture setting

## BS7-AMD2(Pulse/MDB/ICT004)

### BS7 Interface Settings: 3 (ICT004)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON	OFF	
	MDB Interface		OFF	OFF	
★	ICT004 Interface		OFF	ON	
	Reserved		ON	ON	
★	Reserved				ON
					OFF

### BS7 Interface Settings: 3 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	MDB Interface		OFF	OFF	
	ICT004 Interface		OFF	ON	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

### BS7 Interface Settings: 3 (MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★	Pulse Mode		ON	OFF	
	MDB Interface		OFF	OFF	
	ICT004 Interface		OFF	ON	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

### Currency Assign Data

Interface Bill value	ICT004	Pulse	MDB
BV1	DRAMS 1000	DRAMS 1000	DRAMS 1000
BV2	DRAMS 2000	DRAMS 2000	DRAMS 2000

\* Factory configuration has all switches in the OFF position.

Note:(1) Reset the acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.