

## V7-TRY6

### V7 Option Switch Settings: 1 (Pulse/MDB/ICT004U)

Supported bill TRY 5, 10, 20, 50, 100, 200 6bills.

V7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8
★ Reject TRY 5	ON							
★ Accept TRY 5	OFF							
★ Reject TRY 10		ON						
★ Accept TRY 10		OFF						
★ Reject TRY 20			ON					
★ Accept TRY 20			OFF					
★ Reject TRY 50				ON				
★ Accept TRY 50				OFF				
★ Reject TRY 100 & 200					ON			
★ Accept TRY 100 & 200					OFF			
★ Reserved						ON		
★ Reserved						OFF		
★ Harness Disable							ON	
★ Harness Enable							OFF	
★ Inhibit Active High								ON
★ Inhibit Active Low								OFF

◆ Factory configuration has all switches in the OFF position.

### V7 Interface Settings: 2 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ 1 pulse / TRY 5	OFF	OFF		
5 pulses / TRY 5	ON	OFF		
10 pulses / TRY 5	OFF	ON		
20 pulses / TRY 5	ON	ON		
★ 50ms Lo / 50ms Hi			OFF	OFF
60ms Lo / 300ms Hi			ON	OFF
30ms Lo / 50ms Hi			OFF	ON
150ms Lo / 150ms Hi			ON	ON

★ Manufacture setting

## V7-TRY6(Pulse/MDB/ICT004U)

### V7 Interface Settings: 3 (ICT)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
MDB Mode		OFF	OFF	
★ ICT Mode		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

### V7 Interface Settings: 3 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
MDB Mode		OFF	OFF	
ICT Mode		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

### V7 Interface Settings: 3 (MDB)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ MDB Mode		OFF	OFF	
ICT Mode		OFF	ON	
Reserved		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Note: 1.Default setting

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "Sw1" setting.)

### Currency Assign Data

Interface Bill value	ICT	Pulse	MDB
BV1	TRY 5	TRY 5	TRY 5
BV2	TRY 10	TRY 10	TRY 10
BV3	TRY 20	TRY 20	TRY 20
BV4	TRY 50	TRY 50	TRY 50
BV5	TRY 100	TRY 100	TRY 100
BV6	TRY 200	TRY 200	TRY 200